

AUDIOSCAPE MEQ-A



Thank you for purchasing the MEQ-A from AUDIOSCAPE Engineering! Inspired by the famous vintage mid-range equalizer, it is a worthy addition to any studio. It magically brings program material to life with effortless tube warmth. Simply put, there is no setting that sounds anything less than amazing. Let's dig into it's features!

FEATURES

- Transformer Balanced, **Inductor-Based Equalizer** with a **Tube Gain Make-Up Amplifier**
- Stylish **2U Rackmount** with Period-Correct Faceplate & Vintage-Styled Replica Knobs
- Custom, **Hand-Wound USA Made Transformers** (faithful to original specifications) & **Vintage NOS Tubes** in the Audio Path Faithfully Recreate the Sonic Nuances of the Original
- **3 Custom Inductors** (1 for Each Band) Impart a Musical Edge that sets this EQ Circuit in a League of it's Own
- Period-Correct, **Premium Capacitors & Resistors** utilized throughout the circuit. Sourced from US Based Distributors
- **Bypass EQ Switch** on Front Panel to Allow use of the Tube Amplifier Alone to Add Track Warmth & Glue
- **Midrange Dip** Function Unlike any Other EQ Design. Cut Deep or Subtle Depending on the Will of the Operator
- **Neutrik XLR In/Out Connectors** – Built to Last a Lifetime
- **Alpha Potentiometers & Rotary Switches**

SPECS

Freq Response: **15hz-20khz**
EQ Range: **200hz-7khz**
Noise: **-80dB +/-5**
Height: **2U**
Depth: **9 in (229mm)**
Width: **19 in (48cm)**
Weight: **14 lbs**
Power: **120V**
Imp in/out: **6000hm**

EQ SPECS

Lo Band: **+10db from 200hz-1khz**
Mid Cut: **-10db from 200hz-7khz**
Hi Band: **+8db from 1.5khz-7khz**

TUBES:

12ax7 6aq5 6x4